SERVICE MANUAL

FISHER

DIGITAL COMPACT DISC CHANGER

DAC-9050

(EUROPE)

137 349 42

The original service manual of model DAC-9050 refrects the Black version only. This supplement is intended to add the Titan Gray version to the original service manual of WM-570351.

Ref.No.	DAC-9050 (Black)	DAC-9050 (Titan Gray)	Description	Q'ty
	PACKAGE			
	620 204 3715	620 212 7293	Inner Carton	1
	ACCESSORIES			
	620 204 4118	620 212 6807	Assy,Poly Cover	1
	620 204 4088	620 212 6821	Instruction Manual	1
	620 209 3970	620 212 6814	Label,Barcode	1
	CABINET			
3	620 204 3692	620 212 7156	Assy,Cabinet	1
4	620 198 6969	620 212 3943	Assy,Foot	4
6	620 198 7775	620 212 7132	Cover	1
7	620 198 5733	620 212 7262	Lid	1
9	620 198 5726	620 212 7149	Panel,Top	1
10	620 198 7102	620 212 7279	Panel,Front	1
12	620 198 0622	620 212 4162	Button,Power	1
14	620 198 5740	620 212 7286	Button,Eject	1
15	620 198 6983	– – – –	Foot	2
36	620 198 0615	620 212 7316	Knob,Rotary,Volume	1
	CD MECHANISM			
1	620 200 9582	– – – –	Assy,Pickup,Laser,88,CPW	1
	– – – –	620 204 5696	Assy,Pickup,Laser,90,CPW	1

Add this sheet Model DAC-9050 Service Manual (WM-570351).



FISHER Hi-Fi Europa Vertriebs GmbH
Stahlgruberring 4 Tel: 089/420 45-0
8000 München 82 Tlx: 524033

March/'91/1,500/H **Printed in Japan**

REFERENCE No. WM-570695

SERV. 35 890

330

SERVICE MANUAL

FISHER

DIGITAL COMPACT DISC CHANGER

DAC-9050

(EUROPE)



137 349 40

SPECIFICATIONS

System ..... Compact disc digital audio

AUDIO CHARACTERISTICS

Frequency Response ..... 20 Hz ~ 20 kHz ±0.5 dB
Harmonic Distortion
(20 kHz Low Pass Filter) ..... Less than 0.005 % (1 kHz)
Dynamic Range ..... More than 92 dB
S/N Ratio ..... More than 100 dB
Wow and Flutter ..... Below measurable limits
Channel Separation ..... More than 95 dB (1 kHz)
Output Voltage (maximum) ..... 2 Vrms

FUNCTIONS

Disc Selection ..... With DISC NUMBER buttons (1 ~ 5)
Track Selection ..... With FFWD and FBACK buttons or remote control's numbered buttons (0 ~ 9)
Index Selection ..... With SCAN/INDEX ▶| and |◀ buttons (normal play only)
Program Selection ..... With DISC NUMBER buttons (1 ~ 5), FFWD and FBACK buttons, or remote control's numbered buttons (0 ~ 9)
Scanning (fast forward/fast back) 2-speed search with sound
Each/Remain/Total Time Display ..... With DISPLAY button during the PLAY mode
Program Memory ..... 32 selections
Introscan Play ..... 10 seconds/track or 1 ~ 58 seconds, programmable with remote control's numbered buttons (0 ~ 9)
Random Play ..... With the RANDOM PLAY button during the PLAY mode
Repeat Play ..... One track/all tracks/all programmed tracks
Program Reset ..... With CLEAR button
Checking Program ..... With CHECK button (in STOP mode)
Pause ..... Each track
Disc Loading ..... Motor-driven, horizontal loading

DIGITAL SIGNAL PROCESSING

Optical Pickup ..... 3-beam laser
Sampling Frequency ..... 44.1 kHz
Filters ..... 18-bit, 8 times oversampling digital filter
2-pole active filter
D/A Conversion ..... Two 16-bit, linear, D/A converters

GENERAL

Power Requirements (50 Hz) ..... AC 220V
25 Watts
Dimensions (W x H x D) ..... 440 x 150 x 320mm
Weight (approximate) 6.6kg

– Specifications and design are subject to change without notice. –

REFERENCE No. WM-570351

330

FUNCTIONAL BLOCK DIAGRAM



BEFORE USE

To protect the internal laser pickup mechanism from shocks and movement during transport, it has been secured by the white lever, located in the bottom panel of the CD changer.
Slide this lever all the way to RELEASE, before the unit is switched on.



SAFETY CERTIFICATION


CLASS 1 LASER PRODUCT
CAUTION - INVISIBLE LASER RADIATION WHEN OPEN AND INTERLOCKS DEFEATED. AVOID EXPOSURE TO BEAM.
VORSICHT! UNSICHTBARE LASERSTRAHLUNG TRITT AUS, WENN DECKEL GEOFFNET UND WENN SICHERHEITSVERRIEGELUNG UBERBRUCKT IST. NICHT DEM STRAHL AUSSETZEN!
VARNING - OSYNLIG LASERSTRÄLNING NAR DENNA DEL AR OPPNAD OCH SPARR AR URKOPPLAD. STRÅLEN AR FARLIG.
ADVARSEL - USYNLIG LASERSTRÅLING VED ÅBNING, NÅR SIKKERHEDSAFBRYDERE ER UDE AF FUNKTION. UNDGÅ UDSÆTTELSE FOR STRÅLING.

CAUTION – USE OF CONTROLS OR ADJUSTMENTS OR PERFORMANCE OF PROCEDURES OTHER THAN THOSE SPECIFIED HEREIN MAY RESULT IN HAZARDOUS RADIATION EXPOSURE.

THE COMPACT DISC PLAYER SHOULD NOT BE ADJUSTED OR REPAIRED BY ANYONE EXCEPT QUALIFIED SERVICE PERSONNEL.

LASER BEAM RADIATION SPOT



Laser Diode Properties
Material: Ga-Al-As
Wavelength: 755 – 815 nm (25°C)
Laser Output: Continuous Wave max.0.5 mW

CD MECHANISM EXPLODED VIEW



CD MECHANISM PARTS LIST

Ref. No.	Part No.	Description	Q'ty
CD MECHANISM			
1	620 200 9582	Assy,Pickup,Laser,88,CPW	1
2	620 015 8633	Leaf Switch [S7]	1
3	620 030 4290	Spindle Motor [M3]	1
4	620 190 1702	Motor [M4]	1
5	620 183 4819	Chassis Assy	1
6	620 125 1487	Washer M1.9X7.0X0.25	1
7	620 127 7814	Gear Motor	1
8	620 127 9542	Gear Pinion	1
9	620 127 9559	Gear Load B	1
10	620 127 9566	Gear Load S	1
11	620 127 9573	Gear Rack	1
12	620 133 4159	Shaft Pick-UP	2
13	620 196 2697	Spring,Torsion	4
14	620 123 0116	Set Screw V-Cone 2X4	1
15	620 082 7478	Turntable Assy	1

Ref. No.	Part No.	Description	Q'ty
21	411 019 9302	SCR PAN PCS 1.7X2.5	4
22	411 129 0800	SCR FLT PCS 2X5	2
23	411 107 6404	SCR S-TPG PAN 2.6X6	1

NOTES:

1. Parts order must contain Model Number, Part Number and Description.
2. Ordering quantity of screws and resistors must be multiple of 10 pcs.

CABINET EXPLODED VIEW (1)



CABINET EXPLODED VIEW (1)



CABINET PARTS LIST

Ref. No.	Part No.	Description	Q'ty
PACKAGE			
	620 204 3715	Inner Carton	1
	620 200 0329	Pad,Top	1
	620 200 0343	Pad,Bottom	1
	620 059 6596	Patching Sheet	1
	620 148 8012	Sheet Polyethylene	1
ACCESSORIES			
	620 204 4118	Assy,Poly Cover	1
	620 021 7408	RCA Cord 1000mm Black	1
	620 204 4088	Instruction Manual	1
	620 017 7955	Connector 4P Assy	1
	620 152 2624	Certificate Card	1
	620 152 7452	Serial No. Sheet	1
	620 057 8783	Bag Fan	1
	620 062 1175	Tape 12mm	
	620 150 8567	Notes	1
CABINET			
CA103	620 201 1684	Assy,Connector-S,6P	1
CA104	620 201 1691	Assy,Connector-S,2P	1
CA105	620 201 1707	Assy,Connector-S,4P	1
CA106	620 201 1721	Assy,Connector-S,5P	1
CA107	620 201 1738	Assy,Connector-S,6P	1
CA108	620 201 1769	Assy,Connector-S,4P	1
CA110	620 201 1776	Assy,Connector-S,2P	1
	620 198 1131	Label,Safety, (DHHS)	1
	620 054 9950	Label (UL Caution)	1
	620 125 8424	Wire Band	12
	620 150 8567	Notes	1
1	⚠ 620 023 7550	Power Cord	1
2	620 200 2194	Assy,Motor,3V,1W	1
3	620 204 3692	Assy,Cabinet	1
4	620 198 6969	Assy,Foot	2
5	620 198 7928	Assy,Chassis,Lid	1
6	620 198 7775	Cover	1
7	620 198 5733	Lid	1
8	620 198 7843	Plate,Bottom	1
9	620 198 5726	Panel,Top	1
10	620 198 7102	Panel,Front	1
11	620 204 3678	Panel,Rear	1
12	620 198 0622	Button,Power	1
13	620 198 5702	Button,Program	1
14	620 198 5740	Button,Eject	1
15	620 198 6983	Foot	2
16	620 198 7782	Bracket-M,Right	1
17	620 198 7799	Bracket-M,Left	1
18	620 198 7805	Bracket-M,Mechanism,Right	1
19	620 198 7812	Bracket-M,Mechanism,Left	1
20	620 198 7829	Bracket-M,Front	1
21	620 202 1041	Mount-E,PCB	2
22	620 201 4968	Cushion,Button	1
23	620 203 2160	Cushion,Button	1
24	620 203 0326	Adhesive Sheet	1
25	620 196 3380	Gear,Eject	1
26	620 196 3397	Gear,Load	1
27	620 196 3403	Pulley,Gear	1
28	620 196 3373	Belt,Square	1
29	620 199 5466	Lever,Lock,Mechanism	1
30	⚠ 620 201 8614	Power Trans,SEV,30VA	1
31	620 196 4868	Switch,Push,NO,1P-1T (LID)	1
32	620 196 4073	Switch,Leaf (LID)	1
33	620 053 2136	Bushing (MP4N-4)	1
34	620 125 4709	Washer M2.1X3.5X0.5	1
35	⚠ 620 017 1212	AC Socket	1
36	620 198 0615	Knob,Rotary,Volume	1
37	620 201 8973	Bracket-E	1
41	620 206 4512	Assy,PCB,Main	1
42	620 201 5286	Assy,PCB,Trans	1
43	620 201 0328	Assy,PCB,Headphone	1
44	620 201 1257	Assy,PCB,FL	1
45	620 201 1264	Assy,PCB,Switch,Left	1
46	620 201 1271	Assy,PCB,Switch,Right	1
47	620 203 9695	Assy,PCB,Power Switch	1
51	411 019 8909	SCR PAN PCS 1.7X2	2
52	411 020 5508	SCR S-TPG BRZ 2.6X6	2
53	411 020 5706	SCR S-TPG BRZ 2.6X8	6
54	411 020 6802	SCR S-TPG BRZ 3X18	2
55	411 020 7700	SCR S-TPG BRZ 3X6	26
56	411 099 9704	SCR S-TPG BRZ 3X6	8
57	411 020 8004	SCR S-TPG BRZ 3X8	6
58	411 099 9803	SCR S-TPG BRZ 3X8	5
59	411 021 0601	SCR S-TPG BIN 2X5	1
60	411 021 1202	SCR S-TPG BIN 2X8	7
61	411 021 6603	SCR S-TPG BIN 3X8	5
62	411 024 8406	SCR S-TPG TRS 4X8	2
63	411 085 2504	WASHER Out TW 3	2

NOTES:

1. Parts order must contain Model Number, Part Number and Description.
2. Ordering quantity of screws and resistors must be multiple of 10 pcs.

PRODUCT SAFETY NOTICE

Each precaution in this manual should be followed during servicing. Components identified with the IEC symbol ⚠ in the parts list and the schematic diagram designate components in which safety can be of special significance. When replacing a component identified with ⚠, use only the replacement parts designated, or parts with the same ratings of resistance, wattage or voltage that are designated in the parts list in this manual. Leakage-current or resistance measurements must be made to determine that exposed parts are acceptably insulated from the supply circuit before returning the product to the customer.

CD INDEX MECHANISM EXPLODED VIEW



CD INDEX MECHANISM PARTS LIST

Ref. No.	Part No.	Description	Q'ty
MECHANISM			
	620 114 9104	Sheet	2
	620 125 8110	Lug	1
	620 125 8424	Wire Band	8
1	620 125 6673	Washer 4.7X9X0.13	2
2	620 016 9363	Lever Switch 1P2T [S3 ~ S6]	4
3	620 030 4108	Motor (TRAY UP/DOWN) [M1]	1
4	620 030 4115	Motor (Load) (TRAY OPEN) [M2]	1
5	620 084 2501	Slide Plate Assy	1
6	620 085 0896	Lever Index Assy	1
7	620 085 3385	Arm Index Assy	1
8	620 085 6553	Magnet Assy	1
9	620 124 3376	Cushion Rubber	4
10	620 117 1204	Chassis (Load)	1
11	620 119 1530	Holder Disc	1
12	620 127 8514	Gear Wormwheel	1
13	620 127 8521	Gear Index	1
14	620 127 8538	Gear Worm	1
15	620 127 8545	Gear Cam Left	1
16	620 127 8552	Gear Cam Right	1
17	620 127 8569	Gear Pulley	1
18	620 127 8576	Gear Load	1
19	620 127 8583	Gear Pinion	2
20	620 128 3600	Belt (Timing)	1
21	620 128 6540	Belt	2
22	620 129 5948	Support Front	1
23	620 129 5955	Support Rear	1
24	620 129 5962	Flap Disc Cramp	1
25	620 193 6438	Tray	5
26	620 130 6736	Slide Left	1
27	620 130 6743	Slide Right	1
28	620 131 9262	Lever Cam Left	1
29	620 131 9279	Lever Eject	1
30	620 131 9286	Lever Stop	1
31	620 131 9293	Lever Rock	5
32	620 131 9309	Lever Adjust	1
33	620 133 3572	Shaft Gear Worm	1
34	620 133 3589	Shaft Index	1
35	620 133 3596	Pin Adjust	1
36	620 133 3602	Shaft Lever Rock	1
37	620 136 0684	Guide Left	1
38	620 136 0691	Guide Right	1
39	620 136 0707	Guide Plate	1
40	620 136 5887	Cap Gear Pinion	2
41	620 137 9105	Spring Lever Stop	2
42	620 137 9112	Spring Arm Index	1
43	620 137 9129	Spring Lever Adjust	1
44	620 138 6394	Spring Lever Rock	1
45	620 138 6400	Spring Plate	1
46	620 139 1091	Spring Lever Index	1
47	620 130 7122	Slide Plate Left	1
48	620 139 1367	Spring Slide PL Left	1
51	620 079 3001	PCB LED Assy	1
52	620 079 3018	PCB Photo TR. Assy	1
53	620 079 3025	PCB Photo Sense Assy	1
54	620 187 7977	PCB LED 8CM Assy	1
55	620 187 7984	PCB Sens 8CM Assy	1
61	620 122 6249	SCR PAN TPG-2 +M2.6X5.0	5
62	620 122 6324	Screw Washer +2.6X6.0	2
63	620 051 4279	Screw 3X8	1
64	620 051 4316	Screw 3X10	2
65	620 123 1021	Screw Braz. HD. +M2.6X14	4
66	620 122 8397	Screw Tapping +2.0X6.0	1
67	411 020 7007	SCR S-TPG BRZ 3X20	2
68	411 020 5904	SCR S-TPG BRZ 3X10	13
69	411 020 7700	SCR S-TPG BRZ 3X6	6
70	411 020 5508	SCR S-TPG BRZ 2.6X6	5
71	411 022 1904	SCR S-TPG FLT 2.6X6	1
72	411 031 0103	SCR BIN 2.6X3	2
73	411 031 0905	SCR BIN 2.6X4	2
74	411 030 7707	SCR BIN 2X8	2
75	411 063 7309	SCR TPG BIN 2X10	3
76	411 063 8504	SCR TPG BIN 2X8	1
77	412 034 0701	SPECIAL WASHER	1

Ref. No.	Part No.	Description	Q'ty

NOTES:

1. Parts order must contain Model Number, Part Number and Description.
2. Ordering quantity of screws and resistors must be multiple of 10 pcs.

P.C.BOARD PARTS LIST

Ref. No.	Part No.	Description	Q'ty
ASSY,PCB,MAIN			
41	620 206 4512	Assy,PCB,Main	1
	620 021 6807	Pin 1P	1
	620 197 9473	Heat Sink	1
	620 204 0516	Jack,RCA,2P,W/GND	1
	620 201 2308	Wire,Staple,L = 35mm	1
	620 125 8516	Staple 7.5	2
	620 125 8752	Staple 15mm	8
	620 125 8943	Staple 30 mm	1
CN101	620 201 4296	Plug,6P	1
CN102	620 021 8337	Plug 6P	1
CN103	620 021 5954	Plug 6P	1
CN104	620 021 1970	Plug 2P	1
CN105	620 021 5930	Plug 4P	1
CN106	620 021 5947	Plug 5P	1
CN107	620 021 8610	Plug 6P	1
CN108	620 021 8597	Plug 4P	1
CN110	620 021 8306	Plug 2P	1
CN111	620 021 6555	Plug 4P	1
CN501	620 022 1641	Plug 13P	1
CN502	620 201 2339	Plug,12P	1
CN601	620 021 8474	Plug 7P	1
CN602	620 021 8320	Plug 5P	1
CN604	620 021 8313	Plug 3P	1
CN701	620 021 8399	Plug 7P	1
CN702	620 021 8474	Plug 7P	1
CN801	620 021 8450	Plug 3P	1
CN802	620 021 8313	Plug 3P	1
CN901	620 021 6234	Plug 7P	1
CN902	620 021 5930	Plug 4P	1
CN903	620 021 5923	Plug 3P	1
CN904	620 021 5923	Plug 3P	1
L101	620 197 9039	Inductor 100UH K	1
L102	620 026 8752	RF Low Pass Filter	1
L103	620 028 8699	OSC Coil	1
RB103	620 004 5582	Resistor 6X22K J	1
RB104	620 004 5247	Resistor 4X22K J	1
T101	620 202 4349	Terminal,8P,P = 2.5	1
T102	620 202 4332	Terminal,7P,P = 2.5	1
T103	620 202 4318	Terminal,5P,P = 2.5	1
T104	620 202 4271	Terminal,2P,P = 2.5	1
T105	620 202 4271	Terminal,2P,P = 2.5	1
VR101	620 006 1384	Potentiometer 220KB	1
VR102	620 006 1353	Potentiometer 100KB	1
VR103	620 006 1384	Potentiometer 220KB	1
VR104	620 006 1353	Potentiometer 100KB	1
VR105	620 006 1384	Potentiometer 220KB	1
VR106	620 006 1353	Potentiometer 100KB	1
XT101	620 203 4164	Resonator,Xtal,16.9344MHz	1
or	620 201 4265	Resonator,Xtal,16.9344MHz	1
IC101	409 124 6507	IC LA9200NM	1
IC102	409 183 9006	IC YM3815-H	1
IC103	409 020 6205	IC LC3517AM-15	1
IC104	409 204 0609	IC YM3613C	1
IC105	409 195 4204	IC PD0050	1
IC106	409 071 9200	IC TC4075B	1
IC107	409 051 2207	IC TC4049BP	1
IC108	409 070 5401	IC NJM4558	1
IC109	409 070 5401	IC NJM4558	1
IC110	409 070 5401	IC NJM4558	1
IC111	409 070 5401	IC NJM4558	1
IC112	409 183 8504	IC STA341M	1
IC115	409 087 1304	IC LC74HC241	1
IC116	409 018 5500	IC LA6510	1
IC117	409 196 7501	IC LC6538D-4215	1
IC118	409 052 1407	IC TC74HCU04P	1
IC119	409 140 2705	IC LA6501-LR	1
IC123	409 070 7009	IC PCM56P	1
IC124	409 070 7009	IC PCM56P	1
IC128	409 039 7507	IC NJM4558D-D	1
IC129	409 039 7507	IC NJM4558D-D	1
Q101	405 032 3102	TR 2SB911-M	1
Q102	405 019 2708	TR 2SC536-F-NP-AA	1
or	405 019 3804	TR 2SC536-G-NP-AA	1
Q103	405 019 2708	TR 2SC536-F-NP-AA	1
or	405 019 3804	TR 2SC536-G-NP-AA	1
Q104	405 019 2708	TR 2SC536-F-NP-AA	1
or	405 019 3804	TR 2SC536-G-NP-AA	1
Q105	405 019 2708	TR 2SC536-F-NP-AA	1

Ref. No.	Part No.	Description	Q'ty
or	405 019 3804	TR 2SC536-G-NP-AA	1
Q106	405 034 6705	TR DTA114-EF	1
Q107	405 019 2708	TR 2SC536-F-NP-AA	1
or	405 019 3804	TR 2SC536-G-NP-AA	1
Q108	405 019 2708	TR 2SC536-F-NP-AA	1
or	405 019 3804	TR 2SC536-G-NP-AA	1
Q109	405 019 2708	TR 2SC536-F-NP-AA	1
or	405 019 3804	TR 2SC536-G-NP-AA	1
Q110	405 033 5006	TR 2SD1227-M	1
Q111	405 032 3102	TR 2SB911-M	1
Q112	405 033 5006	TR 2SD1227-M	1
Q113	405 032 3102	TR 2SB911-M	1
Q116	405 019 2708	TR 2SC536-F-NP-AA	1
or	405 019 3804	TR 2SC536-G-NP-AA	1
Q120	405 019 2708	TR 2SC536-F-NP-AA	1
or	405 019 3804	TR 2SC536-G-NP-AA	1
Q121	405 019 2708	TR 2SC536-F-NP-AA	1
or	405 019 3804	TR 2SC536-G-NP-AA	1
Q122	405 021 0204	TR 2SD1012-F-SPA-AC	1
or	405 021 0600	TR 2SD1012-G-SPA-AC	1
Q123	405 003 7702	TR 2SA1346	1
Q124	405 003 7702	TR 2SA1346	1
Q125	405 019 2708	TR 2SC536-F-NP-AA	1
or	405 019 3804	TR 2SC536-G-NP-AA	1
Q126	405 019 2708	TR 2SC536-F-NP-AA	1
or	405 019 3804	TR 2SC536-G-NP-AA	1
Q128	405 019 2708	TR 2SC536-F-NP-AA	1
or	405 019 3804	TR 2SC536-G-NP-AA	1
Q129	405 019 2708	TR 2SC536-F-NP-AA	1
or	405 019 3804	TR 2SC536-G-NP-AA	1
Q130	405 019 2708	TR 2SC536-F-NP-AA	1
or	405 019 3804	TR 2SC536-G-NP-AA	1
Q131	405 021 0204	TR 2SD1012-F-SPA-AC	1
or	405 021 0600	TR 2SD1012-G-SPA-AC	1
Q132	405 021 0204	TR 2SD1012-F-SPA-AC	1
or	405 021 0600	TR 2SD1012-G-SPA-AC	1
Q133	405 021 0204	TR 2SD1012-F-SPA-AC	1
or	405 021 0600	TR 2SD1012-G-SPA-AC	1
Q134	405 021 0204	TR 2SD1012-F-SPA-AC	1
or	405 021 0600	TR 2SD1012-G-SPA-AC	1
Q135	405 004 4502	TR 2SA608-F-NP-AA	1
or	405 004 5004	TR 2SA608-G-NP	1
or	405 004 4601	TR 2SA608-F-SPA-AC	1
or	405 004 5103	TR 2SA608-G-SPA-AC	1
Q136	405 019 2708	TR 2SC536-F-NP-AA	1
or	405 019 3804	TR 2SC536-G-NP-AA	1
Q137	405 019 2708	TR 2SC536-F-NP-AA	1
or	405 019 3804	TR 2SC536-G-NP-AA	1
Q138	405 021 0204	TR 2SD1012-F-SPA-AC	1
Q138	405 021 0600	TR 2SD1012-G-SPA-AC	1
Q139	405 021 0204	TR 2SD1012-F-SPA-AC	1
Q139	405 021 0600	TR 2SD1012-G-SPA-AC	1
D101	407 000 3503	VARACTOR DI SVC211SP	1
D102	407 008 7206	DIODE MA700	1
D103	407 125 8209	DIODE HSS271	1
or	407 008 0405	DIODE GMB01-BT	1
D104	407 125 8209	DIODE HSS271	1
or	407 008 0405	DIODE GMB01-BT	1
D105	407 125 8209	DIODE HSS271	1
or	407 008 0405	DIODE GMB01-BT	1
D106	407 125 8209	DIODE HSS271	1
or	407 008 0405	DIODE GMB01-BT	1
D112	407 005 3805	DIODE DS442-BT	1
D113	407 005 3805	DIODE DS442-BT	1
D114	407 005 3805	DIODE DS442-BT	1
D115	407 005 3805	DIODE DS442-BT	1
D116	407 005 3805	DIODE DS442-BT	1
D117	407 005 3805	DIODE DS442-BT	1
D118	407 005 3805	DIODE DS442-BT	1
D119	407 005 3805	DIODE DS442-BT	1
D120	407 005 3805	DIODE DS442-BT	1
D121	407 125 8209	DIODE HSS271	1
or	407 008 0405	DIODE GMB01-BT	1
D122	407 125 8209	DIODE HSS271	1
or	407 008 0405	DIODE GMB01-BT	1
D124	407 125 8209	DIODE HSS271	1
or	407 008 0405	DIODE GMB01-BT	1
D128	407 125 8209	DIODE HSS271	1
or	407 008 0405	DIODE GMB01-BT	1

P.C.BOARD PARTS LIST (Continued)

Ref. No.	Part No.	Description				Q'ty
D301	407 125 8209	DIODE HSS271				1
or	407 008 0405	DIODE GMB01-BT				1
C101	403 030 6309	CERAMIC	68P	J	50V	1
C102	403 071 2001	CERAMIC	180P	K	50V	1
C103	403 048 7701	ELECT	0.47U	M	50V	1
C104	403 030 6309	CERAMIC	68P	J	50V	1
C105	403 059 5604	POLYESTER	0.022U	J	50V	1
C106	403 057 0908	POLYESTER	0.01U	K	50V	1
C107	403 071 6207	CERAMIC	220P	K	50V	1
C108	403 060 5808	POLYESTER	3300P	J	50V	1
C109	403 087 2507	STYRENE	1000P	J	50V	1
C110	403 057 0908	POLYESTER	0.01U	K	50V	1
C111	403 067 5603	MT-COMPO	0.1U	J	50V	1
C112	403 049 5409	ELECT	10U	M	50V	1
C113	403 072 2703	CERAMIC	0.022U	Z	50V	1
C114	403 075 4506	CERAMIC	820P	K	50V	1
C115	403 048 7701	ELECT	0.47U	M	50V	1
C116	403 067 7201	MT-COMPO	0.033U	J	50V	1
C117	403 072 2703	CERAMIC	0.022U	Z	50V	1
C118	403 067 5603	MT-COMPO	0.1U	J	50V	1
C121	403 038 2402	ELECT	100U	M	6.3V	1
C122	403 038 2402	ELECT	100U	M	6.3V	1
C123	403 049 5409	ELECT	10U	M	50V	1
C124	403 026 2209	CERAMIC	47P	J	50V	1
C125	403 026 2209	CERAMIC	47P	J	50V	1
C126	403 072 2703	CERAMIC	0.022U	Z	50V	1
C127	403 044 0300	ELECT	47U	M	16V	1
C128	403 057 0908	POLYESTER	0.01U	K	50V	1
C129	403 059 3303	POLYESTER	2200P	J	50V	1
C131	403 067 6204	MT-COMPO	0.15U	J	50V	1
C132	403 067 6709	MT-COMPO	0.22U	J	50V	1
C133	403 067 7805	MT-COMPO	0.47U	J	50V	1
C134	403 085 6408	NP-ELECT	4.7U	M	16V	1
C135	403 049 1609	ELECT	1U	M	50V	1
C136	403 067 5900	MT-COMPO	0.12U	J	50V	1
C137	403 069 8404	CERAMIC	0.01U	Z	50V	1
C138	403 069 8404	CERAMIC	0.01U	Z	50V	1
C139	403 044 0300	ELECT	47U	M	16V	1
C140	403 072 4707	CERAMIC	270P	K	50V	1
C141	403 049 1609	ELECT	1U	M	50V	1
C142	403 059 5604	POLYESTER	0.022U	J	50V	1
C143	403 067 6709	MT-COMPO	0.22U	J	50V	1
C144	403 067 8307	MT-COMPO	0.68U	J	50V	1
C145	403 044 0300	ELECT	47U	M	16V	1
C146	403 044 0300	ELECT	47U	M	16V	1
C147	403 044 0300	ELECT	47U	M	16V	1
C148	403 044 0300	ELECT	47U	M	16V	1
C149	403 050 1209	ELECT	2.2U	M	50V	1
C150	403 038 2402	ELECT	100U	M	6.3V	1
C151	403 057 7204	POLYESTER	0.012U	J	50V	1
C152	403 057 7204	POLYESTER	0.012U	J	50V	1
C153	403 059 3303	POLYESTER	2200P	J	50V	1
C154	403 086 2706	NP-ELECT	1U	M	50V	1
C155	403 059 3303	POLYESTER	2200P	J	50V	1
C156	403 059 5604	POLYESTER	0.022U	J	50V	1
C159	403 049 1609	ELECT	1U	M	50V	1
C164	403 121 9509	CERAMIC	0.1U	Z	50V	1
C165	403 039 7802	ELECT	100U	M	10V	1
C166	403 086 2706	NP-ELECT	1U	M	50V	1
C168	403 067 5603	MT-COMPO	0.1U	J	50V	1
C169	403 051 2007	ELECT	4.7U	M	50V	1
C170	403 044 0201	ELECT	47U	M	16V	1
C171	403 044 0201	ELECT	47U	M	16V	1
C172	403 086 2706	NP-ELECT	1U	M	50V	1
C173	403 086 2706	NP-ELECT	1U	M	50V	1
C174	403 067 5603	MT-COMPO	0.1U	J	50V	1
C175	403 067 5603	MT-COMPO	0.1U	J	50V	1
C176	403 069 8404	CERAMIC	0.01U	Z	50V	1
C177	403 072 2703	CERAMIC	0.022U	Z	50V	1
C178	403 072 2703	CERAMIC	0.022U	Z	50V	1
C180	403 067 5702	MT-COMPO	1U	J	50V	1
C181	403 049 5409	ELECT	10U	M	50V	1
C182	403 059 5604	POLYESTER	0.022U	J	50V	1
C183	403 072 2703	CERAMIC	0.022U	Z	50V	1
C184	403 038 2402	ELECT	100U	M	6.3V	1
C185	403 019 7303	CERAMIC	27P	J	50V	1
C186	403 017 7404	CERAMIC	22P	J	50V	1
C187	403 072 2703	CERAMIC	0.022U	Z	50V	1
C188	403 038 2402	ELECT	100U	M	6.3V	1

Ref. No.	Part No.	Description				Q'ty
C189	403 044 0300	ELECT	47U	M	16V	1
C190	403 044 0300	ELECT	47U	M	16V	1
C191	403 044 0300	ELECT	47U	M	16V	1
C192	403 044 0300	ELECT	47U	M	16V	1
C193	403 049 5508	ELECT	10U	M	50V	1
C194	403 049 5508	ELECT	10U	M	50V	1
C195	403 049 5508	ELECT	10U	M	50V	1
C196	403 049 5508	ELECT	10U	M	50V	1
C199	403 074 9205	CERAMIC	680P	K	50V	1
C200	403 074 9205	CERAMIC	680P	K	50V	1
C201	403 058 0808	POLYESTER	1500P	J	50V	1
C202	403 058 0808	POLYESTER	1500P	J	50V	1
C203	403 057 0908	POLYESTER	0.01U	K	50V	1
C204	403 057 0908	POLYESTER	0.01U	K	50V	1
C205	403 057 0908	POLYESTER	0.01U	K	50V	1
C206	403 057 0908	POLYESTER	0.01U	K	50V	1
C207	403 058 0808	POLYESTER	1500P	J	50V	1
C208	403 058 0808	POLYESTER	1500P	J	50V	1
C213	403 085 6408	NP-ELECT	4.7U	M	16V	1
C214	403 085 6408	NP-ELECT	4.7U	M	16V	1
C217	403 086 2706	NP-ELECT	1U	M	50V	1
C226	403 044 0300	ELECT	47U	M	16V	1
C227	403 044 0300	ELECT	47U	M	16V	1
C230	403 072 2703	CERAMIC	0.022U	Z	50V	1
C241	403 044 0300	ELECT	47U	M	16V	1
C242	403 044 0300	ELECT	47U	M	16V	1
C243	403 067 7805	MT-COMPO	0.47U	J	50V	1
C244	403 074 2701	CERAMIC	0.047U	Z	50V	1
C245	403 072 2703	CERAMIC	0.022U	Z	50V	1
C247	403 028 1705	CERAMIC	56P	J	50V	1
C249	403 072 2703	CERAMIC	0.022U	Z	50V	1
C251	403 072 2703	CERAMIC	0.022U	Z	50V	1
C252	403 049 1609	ELECT	1U	M	50V	1
R101	401 027 2600	CARBON	5.6K	JA	1/6W	1
R102	401 026 4902	CARBON	330K	JA	1/6W	1
R103	401 027 2303	CARBON	560	JA	1/6W	1
R104	401 026 9907	CARBON	4.7K	JA	1/6W	1
R105	401 027 9005	CARBON	82K	JA	1/6W	1
R106	401 027 5908	CARBON	68K	JA	1/6W	1
R107	401 026 4308	CARBON	3.3K	JA	1/6W	1
R108	401 026 9907	CARBON	4.7K	JA	1/6W	1
R109	401 025 7409	CARBON	220	JA	1/6W	1
R110	401 025 8208	CARBON	22K	JA	1/6W	1
R111	401 025 1605	CARBON	1.5K	JA	1/6W	1
R112	401 020 0801	CARBON	470	JA	1/4W	1
R113	401 025 7805	CARBON	2.2K	JA	1/6W	1
R114	401 024 7707	CARBON	100K	JA	1/6W	1
R115	401 024 7707	CARBON	100K	JA	1/6W	1
R116	401 024 7707	CARBON	100K	JA	1/6W	1
R117	401 024 7400	CARBON	10K	JA	1/6W	1
R118	401 020 2904	CARBON	47K	JA	1/4W	1
R119	401 026 7408	CARBON	39K	JA	1/6W	1
R120	401 025 2305	CARBON	150K	JA	1/6W	1
R121	401 024 7707	CARBON	100K	JA	1/6W	1
R122	401 024 7004	CARBON	1K	JA	1/6W	1
R123	401 025 8703	CARBON	220K	JA	1/6W	1
R124	401 027 0309	CARBON	47K	JA	1/6W	1
R125	401 026 9907	CARBON	4.7K	JA	1/6W	1
R126	401 026 0607	CARBON	270	JA	1/6W	1
R127	401 027 2600	CARBON	5.6K	JA	1/6W	1
R128	401 026 7408	CARBON	39K	JA	1/6W	1
R129	401 023 3700	CARBON	82K	JA	1/4W	1
R130	401 027 0309	CARBON	47K	JA	1/6W	1
R131	401 024 9701	CARBON	12K	JA	1/6W	1
R132	401 027 2600	CARBON	5.6K	JA	1/6W	1
R133	401 027 0309	CARBON	47K	JA	1/6W	1
R134	401 020 2904	CARBON	47K	JA	1/4W	1
R135	401 020 2904	CARBON	47K	JA	1/4W	1
R136	401 024 7707	CARBON	100K	JA	1/6W	1
R137	401 024 7400	CARBON	10K	JA	1/6W	1
R138	401 024 6700	CARBON	100	JA	1/6W	1
R139	401 027 3201	CARBON	560K	JA	1/6W	1
R140	401 027 6103	CARBON	680K	JA	1/6W	1
R141	401 025 0004	CARBON	120K	JA	1/6W	1
R145	401 026 1307	CARBON	27K	JA	1/6W	1
R146	401 025 8703	CARBON	220K	JA	1/6W	1
R147	401 025 8703	CARBON	220K	JA	1/6W	1
R148	401 026 1307	CARBON	27K	JA	1/6W	1
R149	401 026 1307	CARBON	27K	JA	1/6W	1

P.C.BOARD PARTS LIST (Continued)

Ref. No.	Part No.	Description		Q'ty
R150	401 025 8208	CARBON	22K JA 1/6W	1
R151	401 025 8208	CARBON	22K JA 1/6W	1
R152	401 025 8208	CARBON	22K JA 1/6W	1
R153	401 027 0309	CARBON	47K JA 1/6W	1
R154	401 024 7400	CARBON	10K JA 1/6W	1
R155	401 025 8208	CARBON	22K JA 1/6W	1
R156	401 027 0309	CARBON	47K JA 1/6W	1
R157	401 027 9005	CARBON	82K JA 1/6W	1
R158	401 027 5205	CARBON	680 JA 1/6W	1
R159	401 026 4605	CARBON	33K JA 1/6W	1
R160	401 026 4308	CARBON	3.3K JA 1/6W	1
R161	401 026 1307	CARBON	27K JA 1/6W	1
R162	401 027 2600	CARBON	5.6K JA 1/6W	1
R163	401 027 2600	CARBON	5.6K JA 1/6W	1
R164	401 026 7408	CARBON	39K JA 1/6W	1
R165	401 026 1000	CARBON	2.7K JA 1/6W	1
R166	401 026 4605	CARBON	33K JA 1/6W	1
R167	401 025 8208	CARBON	22K JA 1/6W	1
R168	401 027 0309	CARBON	47K JA 1/6W	1
R169	401 026 1604	CARBON	270K JA 1/6W	1
R170	401 024 7400	CARBON	10K JA 1/6W	1
R171	401 027 5205	CARBON	680 JA 1/6W	1
R172	401 025 8208	CARBON	22K JA 1/6W	1
R173	401 025 7805	CARBON	2.2K JA 1/6W	1
R174	401 024 7400	CARBON	10K JA 1/6W	1
R175	401 024 7707	CARBON	100K JA 1/6W	1
R176	401 024 7707	CARBON	100K JA 1/6W	1
R177	401 024 7707	CARBON	100K JA 1/6W	1
R178	401 024 7707	CARBON	100K JA 1/6W	1
R179	401 012 9300	CARBON	1M JA 1/4W	1
R180	401 025 8703	CARBON	220K JA 1/6W	1
R181	401 024 7400	CARBON	10K JA 1/6W	1
R182	401 025 8703	CARBON	220K JA 1/6W	1
R183	401 025 8703	CARBON	220K JA 1/6W	1
R184	401 027 9302	CARBON	820K JA 1/6W	1
R185	401 019 3004	CARBON	39K JA 1/4W	1
R186	401 024 7400	CARBON	10K JA 1/6W	1
R187	401 025 8208	CARBON	22K JA 1/6W	1
R188	401 027 0507	CARBON	470K JA 1/6W	1
R189	401 025 3807	CARBON	180 JA 1/6W	1
R190	401 019 9600	CARBON	47 JA 1/4W	1
R191	401 024 7707	CARBON	100K JA 1/6W	1
R192	401 024 7707	CARBON	100K JA 1/6W	1
R193	401 027 3201	CARBON	560K JA 1/6W	1
R194	401 027 3201	CARBON	560K JA 1/6W	1
R195	401 026 1307	CARBON	27K JA 1/6W	1
R196	401 025 7805	CARBON	2.2K JA 1/6W	1
R197	401 026 1307	CARBON	27K JA 1/6W	1
R198	401 015 6504	CARBON	2.2 JA 1/4W	1
R199	401 013 7305	CARBON	120K JA 1/4W	1
R214	401 025 8703	CARBON	220K JA 1/6W	1
R215	401 024 7004	CARBON	1K JA 1/6W	1
R216	401 024 7707	CARBON	100K JA 1/6W	1
R217	401 016 4806	CARBON	22K JA 1/4W	1
R226	401 026 9907	CARBON	4.7K JA 1/6W	1
R227	401 025 8208	CARBON	22K JA 1/6W	1
R228	401 025 8703	CARBON	220K JA 1/6W	1
R229	401 024 7004	CARBON	1K JA 1/6W	1
R230	401 027 0309	CARBON	47K JA 1/6W	1
R231	401 024 8001	CARBON	1M JA 1/6W	1
R232	401 024 7004	CARBON	1K JA 1/6W	1
R233	401 026 1604	CARBON	270K JA 1/6W	1
R234	401 026 1604	CARBON	270K JA 1/6W	1
R235	401 025 8703	CARBON	220K JA 1/6W	1
R236	401 027 5502	CARBON	6.8K JA 1/6W	1
R237	401 027 5502	CARBON	6.8K JA 1/6W	1
R238	401 024 7004	CARBON	1K JA 1/6W	1
R239	401 024 6403	CARBON	10 JA 1/6W	1
R240	401 024 6007	CARBON	1.5 JA 1/6W	1
R241	401 025 3807	CARBON	180 JA 1/6W	1
R242	401 024 6007	CARBON	1.5 JA 1/6W	1
R243	401 025 8208	CARBON	22K JA 1/6W	1
R244	401 024 6700	CARBON	100 JA 1/6W	1
R245	401 025 8208	CARBON	22K JA 1/6W	1
R246	401 026 4605	CARBON	33K JA 1/6W	1
R247	401 027 0309	CARBON	47K JA 1/6W	1
R248	401 027 0309	CARBON	47K JA 1/6W	1
R249	401 027 3003	CARBON	56K JA 1/6W	1
R250	401 028 0308	CARBON	91K JA 1/6W	1
R251	401 025 0004	CARBON	120K JA 1/6W	1
R252	401 025 0004	CARBON	120K JA 1/6W	1
R253	401 025 8208	CARBON	22K JA 1/6W	1
R254	401 025 8208	CARBON	22K JA 1/6W	1
R255	401 025 5405	CARBON	2.2 JA 1/6W	1
R256	401 025 5405	CARBON	2.2 JA 1/6W	1
R257	401 027 5502	CARBON	6.8K JA 1/6W	1
R258	401 025 4200	CARBON	1.8K JA 1/6W	1
R259	401 027 5502	CARBON	6.8K JA 1/6W	1
R260	401 024 6403	CARBON	10 JA 1/6W	1
R261	401 025 3807	CARBON	180 JA 1/6W	1
R262	401 024 6007	CARBON	1.5 JA 1/6W	1
R263	401 027 5502	CARBON	6.8K JA 1/6W	1
R264	401 027 5502	CARBON	6.8K JA 1/6W	1
R265	401 025 4200	CARBON	1.8K JA 1/6W	1
R266	401 024 6007	CARBON	1.5 JA 1/6W	1
R267	401 025 3807	CARBON	180 JA 1/6W	1
R268	401 024 6403	CARBON	10 JA 1/6W	1
R269	401 025 8703	CARBON	220K JA 1/6W	1
R270	401 027 3003	CARBON	56K JA 1/6W	1
R271	401 025 3807	CARBON	180 JA 1/6W	1
R272	401 025 8208	CARBON	22K JA 1/6W	1
R273	401 025 8208	CARBON	22K JA 1/6W	1
R281	401 025 8208	CARBON	22K JA 1/6W	1
R282	401 012 5708	CARBON	1K JA 1/4W	1
R283	401 012 4503	CARBON	100 JA 1/4W	1
R284	401 024 6700	CARBON	100 JA 1/6W	1
R285	401 025 1605	CARBON	1.5K JA 1/6W	1
R286	401 025 1605	CARBON	1.5K JA 1/6W	1
R287	401 025 1605	CARBON	1.5K JA 1/6W	1
R288	401 025 3807	CARBON	180 JA 1/6W	1
R289	401 024 7707	CARBON	100K JA 1/6W	1
R290	401 024 6700	CARBON	100 JA 1/6W	1
R291	401 024 6700	CARBON	100 JA 1/6W	1
R292	401 024 6700	CARBON	100 JA 1/6W	1
R293	401 024 6700	CARBON	100 JA 1/6W	1
R294	401 024 8001	CARBON	1M JA 1/6W	1
R295	401 012 4503	CARBON	100 JA 1/4W	1
R296	401 012 4503	CARBON	100 JA 1/4W	1
R297	401 012 4503	CARBON	100 JA 1/4W	1
R298	401 012 4503	CARBON	100 JA 1/4W	1
R299	401 024 6700	CARBON	100 JA 1/6W	1
R300	401 026 9303	CARBON	47 JA 1/6W	1
R301	401 024 6700	CARBON	100 JA 1/6W	1
R302	401 026 9303	CARBON	47 JA 1/6W	1
R303	401 024 6403	CARBON	10 JA 1/6W	1
R304	401 024 6403	CARBON	10 JA 1/6W	1
R305	401 024 6403	CARBON	10 JA 1/6W	1
R306	401 024 6403	CARBON	10 JA 1/6W	1
R319	401 014 4105	CARBON	1.5K JA 1/4W	1
R320	401 025 1605	CARBON	1.5K JA 1/6W	1
R321	401 025 1605	CARBON	1.5K JA 1/6W	1
R322	401 025 1605	CARBON	1.5K JA 1/6W	1
R323	401 025 1605	CARBON	1.5K JA 1/6W	1
R324	401 025 1605	CARBON	1.5K JA 1/6W	1
R325	401 026 2908	CARBON	3K JA 1/6W	1
R326	401 026 2908	CARBON	3K JA 1/6W	1
R327	401 025 8703	CARBON	220K JA 1/6W	1
R328	401 025 8703	CARBON	220K JA 1/6W	1
R329	401 025 0608	CARBON	1.3K JA 1/6W	1
R330	401 025 0608	CARBON	1.3K JA 1/6W	1
R333	401 027 0309	CARBON	47K JA 1/6W	1
R334	401 027 0309	CARBON	47K JA 1/6W	1
R335	401 025 7805	CARBON	2.2K JA 1/6W	1
R336	401 025 7805	CARBON	2.2K JA 1/6W	1
R337	401 027 5502	CARBON	6.8K JA 1/6W	1
R338	401 027 5502	CARBON	6.8K JA 1/6W	1
R339	401 027 5502	CARBON	6.8K JA 1/6W	1
R340	401 027 5502	CARBON	6.8K JA 1/6W	1
R341	401 027 5502	CARBON	6.8K JA 1/6W	1
R342	401 027 5502	CARBON	6.8K JA 1/6W	1
R343	401 025 8208	CARBON	22K JA 1/6W	1
R344	401 026 4308	CARBON	3.3K JA 1/6W	1
R345	401 024 7400	CARBON	10K JA 1/6W	1
R346	401 022 3107	CARBON	6.8K JA 1/4W	1
R347	401 026 9907	CARBON	4.7K JA 1/6W	1
R348	401 024 7707	CARBON	100K JA 1/6W	1
R349	401 024 7400	CARBON	10K JA 1/6W	1
R350	401 024 7707	CARBON	100K JA 1/6W	1

P.C.BOARD PARTS LIST (Continued)

Ref. No.	Part No.	Description	Q'ty
R351	401 024 7004	CARBON 1K JA 1/6W	1
R352	401 024 7004	CARBON 1K JA 1/6W	1
R353	401 025 7409	CARBON 220 JA 1/6W	1
R354	401 025 7409	CARBON 220 JA 1/6W	1
R355	401 027 5502	CARBON 6.8K JA 1/6W	1
R356	401 027 5502	CARBON 6.8K JA 1/6W	1
R357	401 024 6403	CARBON 10 JA 1/6W	1
R358	401 024 6403	CARBON 10 JA 1/6W	1
R362	401 024 6700	CARBON 100 JA 1/6W	1
R364	401 025 8208	CARBON 22K JA 1/6W	1
R365	401 013 7305	CARBON 120K JA 1/4W	1
R366	401 026 1604	CARBON 270K JA 1/6W	1
R380	401 024 6700	CARBON 100 JA 1/6W	1
R381	401 024 6700	CARBON 100 JA 1/6W	1
R382	401 024 6700	CARBON 100 JA 1/6W	1
R383	401 024 6700	CARBON 100 JA 1/6W	1
ASSY,PCB,TRANS			
42	620 201 5286	Assy,PCB,Trans	1
	620 017 2738	Fuse Clip	10
	620 022 2587	EC Terminal 1P	2
	⚠ 423 003 9809	~~FUSE 250V T0.63A [F1, F2]~~	2
	⚠ 423 004 3301	FUSE 250V T0.8A [F3, F4]	2
	⚠ 423 006 4702	FUSE 250V T2.5A [F5]	1
	411 020 8004	SCR S-TPG BRZ 3X8	5
	620 203 9909	Terminal,Wrapper,5P	1
	620 202 4943	Terminal,Wrapper,4P	1
	620 201 3589	Label,Fuse,800X2	1
	620 053 7247	Plate Heat Sink	1
	620 053 9241	Plate Heat Sink	4
	620 054 8175	Label	1
	620 055 1243	Label (Fuse)	1
CA901	620 202 0594	Assy,Connector-S,7P	1
CA902	620 202 0600	Assy,Connector-S,4P	1
CA903	620 202 0617	Assy,Connector-S,3P	1
CA904	620 202 0624	Assy,Connector-S,3P	1
CA905	620 202 5698	Assy,Terminal,1P	1
CN506	620 021 8597	Plug 4P	1
CN603	620 021 8306	Plug 2P	1
CN703	620 021 8306	Plug 2P	1
IC901	409 070 4404	IC NJM2043DD	1
IC902	409 169 7804	IC NJM78M05FA	1
IC903	409 169 7804	IC NJM78M05FA	1
IC904	409 050 1706	IC TA79L005P	1
Q901	405 027 0505	TR 2SK246-GR	1
Q902	405 035 7107	TR 2SD1913-R	1
or	405 035 7206	TR 2SD1913-S	1
Q903	405 027 0505	TR 2SK246-GR	1
Q904	405 052 8002	TR 2SB1274-R	1
or	405 052 8101	TR 2SB1274-S	1
Q905	405 019 2708	TR 2SC536-F-NP-AA	1
or	405 019 3804	TR 2SC536-G-NP-AA	1
Q906	405 004 4502	TR 2SA608-F-NP-AA	1
or	405 004 5103	TR 2SA608-G-SPA-AC	1
Q907	405 019 2708	TR 2SC536-F-NP-AA	1
or	405 019 3804	TR 2SC536-G-NP-AA	1
Q908	405 035 7107	TR 2SD1913-R	1
or	405 035 7206	TR 2SD1913-S	1
Q909	405 052 8002	TR 2SB1274-R	1
or	405 052 8101	TR 2SB1274-S	1
Q910	405 032 3102	TR 2SB911-M	1
D901	407 003 5306	DIODE DBA10B	1
D902	407 004 9105	DIODE DSF10C-BT	1
D903	407 004 9105	DIODE DSF10C-BT	1
D904	407 050 7308	ZENER DIODE GZA8.2Y-BT	1
D905	407 049 6305	ZENER DIODE GZA12Y-BT	1
D906	407 049 6305	ZENER DIODE GZA12Y-BT	1
D907	407 125 8209	DIODE HSS271	1
or	407 008 0405	DIODE GMB01-BT	1
D908	407 005 2006	DIODE DS135D-KB1	1
D909	407 005 2006	DIODE DS135D-KB1	1
D910	407 005 2006	DIODE DS135D-KB1	1
D911	407 005 2006	DIODE DS135D-KB1	1
D912	407 088 6502	DIODE MPG06D-PKG3	1
D913	407 088 6502	DIODE MPG06D-PKG3	1
D914	407 049 5902	ZENER DIODE GZA11X	1
D915	407 049 5902	ZENER DIODE GZA11X	1
D916	407 050 0200	ZENER DIODE GZA24Z-BT	1
D917	407 050 5502	ZENER DIODE GZA5.6Y-BT	1

Ref. No.	Part No.	Description	Q'ty
C903	403 074 2701	CERAMIC 0.047U Z 50V	1
C904	403 074 2701	CERAMIC 0.047U Z 50V	1
C905	403 074 2701	CERAMIC 0.047U Z 50V	1
C906	403 074 2701	CERAMIC 0.047U Z 50V	1
C907	403 046 0605	ELECT 2200U M 25V	1
C908	403 046 0605	ELECT 2200U M 25V	1
C909	403 042 3600	ELECT 100U M 16V	1
C910	403 042 3600	ELECT 100U M 16V	1
C911	403 046 4603	ELECT 33U M 25V	1
C912	403 046 4603	ELECT 33U M 25V	1
C913	403 043 7102	ELECT 330U M 16V	1
C914	403 043 7102	ELECT 330U M 16V	1
C915	403 049 1609	ELECT 1U M 50V	1
C916	403 069 8404	CERAMIC 0.01U Z 50V	1
C917	403 039 7901	ELECT 100U M 10V	1
C918	403 039 4504	ELECT 470U M 6.3V	1
C919	403 049 5508	ELECT 10U M 50V	1
C920	403 046 0605	ELECT 2200U M 25V	1
C921	403 046 0605	ELECT 2200U M 25V	1
C922	403 047 4305	ELECT 47U M 25V	1
C923	403 047 4305	ELECT 47U M 25V	1
C924	403 042 3600	ELECT 100U M 16V	1
C925	403 042 3600	ELECT 100U M 16V	1
C926	403 042 3600	ELECT 100U M 16V	1
C927	403 042 3600	ELECT 100U M 16V	1
C928	403 039 7901	ELECT 100U M 10V	1
C929	403 039 7901	ELECT 100U M 10V	1
C930	403 049 7304	ELECT 100U M 50V	1
C931	403 052 8107	ELECT 100U M 35V	1
C932	403 052 6905	ELECT 10U M 35V	1
C933	403 054 1304	ELECT 47U M 35V	1
C934	403 072 2703	CERAMIC 0.022U Z 50V	1
R901	401 011 8908	CARBON 1 JA 1/4W	1
R902	401 011 8908	CARBON 1 JA 1/4W	1
R903	401 063 1308	OXIDE-MT 680 JA 1W	1
R904	401 024 7400	CARBON 10K JA 1/6W	1
R905	401 017 9305	CARBON 3K JA 1/4W	1
R906	401 017 9305	CARBON 3K JA 1/4W	1
R907	401 017 9305	CARBON 3K JA 1/4W	1
R908	401 017 9305	CARBON 3K JA 1/4W	1
R909	401 054 8804	OXIDE-MT 1K JA 1/2W	1
R910	401 025 8208	CARBON 22K JA 1/6W	1
R911	401 025 8208	CARBON 22K JA 1/6W	1
R912	401 024 7707	CARBON 100K JA 1/6W	1
R913	401 024 7400	CARBON 10K JA 1/6W	1
R914	401 024 7707	CARBON 100K JA 1/6W	1
R915	401 025 8208	CARBON 22K JA 1/6W	1
R916	401 024 9008	CARBON 120 JA 1/6W	1
R917	401 024 9008	CARBON 120 JA 1/6W	1
R918	401 024 9008	CARBON 120 JA 1/6W	1
R919	401 024 9008	CARBON 120 JA 1/6W	1
R920	401 059 1800	OXIDE-MT 15 JA 1W	1
R921	402 015 4606	FUSIBLE RES 4.7 J- 1/4W	1
R922	401 056 5207	OXIDE-MT 56 JA 1/2W	1
R923	401 013 5608	CARBON 1.2K JA 1/4W	1
R924	401 024 7400	CARBON 10K JA 1/6W	1
R925	402 016 5404	FUSIBLE RES 4.7 J- 1/2W	1
R926	402 016 5404	FUSIBLE RES 4.7 J- 1/2W	1
ASSY,PCB,HEADPHONE			
43	620 201 0328	Assy,PCB,Headphone	1
	620 006 2954	VR 2X50KA	1
	620 017 2066	Jack 3P W/Boss	1
	620 022 3492	Terminal Lug	1
CA801	620 201 2407	Assy,Connector-S,3P	1
CA802	620 201 2414	Assy,Connector-S,3P	1
IC801	409 039 7309	IC NJM4556S	1
C801	403 071 6207	CERAMIC 220P K 50V	1
C802	403 071 6207	CERAMIC 220P K 50V	1
C803	403 074 2701	CERAMIC 0.047U Z 50V	1
C804	403 044 0300	ELECT 47U M 16V	1
C805	403 044 0300	ELECT 47U M 16V	1
C806	403 086 5509	NP-ELECT 2.2U M 50V	1
C807	403 086 5509	NP-ELECT 2.2U M 50V	1
C808	403 074 2701	CERAMIC 0.047U Z 50V	1
R801	401 024 7004	CARBON 1K JA 1/6W	1
R802	401 024 7004	CARBON 1K JA 1/6W	1
R803	401 012 5708	CARBON 1K JA 1/4W	1
R804	401 024 7004	CARBON 1K JA 1/6W	1

P.C.BOARD PARTS LIST (Continued)

Ref. No.	Part No.	Description	Q'ty
R805	401 024 9701	CARBON 12K JA 1/6W	1
R806	401 024 9701	CARBON 12K JA 1/6W	1
R807	401 027 0309	CARBON 47K JA 1/6W	1
R808	401 027 0309	CARBON 47K JA 1/6W	1
R809	401 012 4503	CARBON 100 JA 1/4W	1
R810	401 012 4503	CARBON 100 JA 1/4W	1
ASSY,PCB,FL			
44	620 201 1257	Assy,PCB,FL	1
	620 201 5255	Cushion,Rubber	2
	620 201 4746	Fluorescent Tube,12BT28GK	1
CA501	620 201 1332	Assy,Connector-S,13P	1
CA502	620 201 1349	Assy,Connector-S,12P	1
CA506	620 201 1387	Assy,Connector-S,4P	1
ASSY,PCB,SWITCH,LEFT			
45	620 201 1264	Assy,PCB,Switch,Left	1
	620 198 0875	Spacer	1
CA701	620 201 1646	Assy,Connector-S,7P	1
CA702	620 201 1653	Assy,Connector-S,7P	1
CA703	620 201 1660	Assy,Connector-S,2P	1
PL702	620 030 8083	Lamp	1
SW701	620 201 2353	Switch,Tact 160G (DISPLAY)	1
SW702	620 201 2353	Switch,Tact 160G (REPEAT)	1
SW703	620 201 2353	Switch,Tact 160G (RANDOM)	1
SW704	620 201 2353	Switch,Tact 160G (MEMORY)	1
SW705	620 201 2353	Switch,Tact 160G (CLEAR)	1
SW706	620 201 2353	Switch,Tact 160G (CHECK)	1
SW707	620 201 2353	Switch,Tact 160G (DISK 1)	1
SW708	620 201 2353	Switch,Tact 160G (DISK 2)	1
SW709	620 201 2353	Switch,Tact 160G (DISK 3)	1
SW710	620 201 2353	Switch,Tact 160G (DISK 4)	1
SW711	620 201 2353	Switch,Tact 160G (DISK 5)	1
SW712	620 201 2353	Switch,Tact 160G (INTRO)	1
D701	407 125 8209	DIODE HSS271	1
or	407 008 0405	DIODE GMB01-BT	1
D702	407 125 8209	DIODE HSS271	1
or	407 008 0405	DIODE GMB01-BT	1
D703	407 125 8209	DIODE HSS271	1
or	407 008 0405	DIODE GMB01-BT	1
D704	407 125 8209	DIODE HSS271	1
or	407 008 0405	DIODE GMB01-BT	1
ASSY,PCB,SWITCH,RIGHT			
46	620 201 1271	Assy,PCB,Switch,Right	1
	620 198 0875	Spacer	1
CA601	620 201 1608	Assy,Connector-S,7P	1
CA602	620 201 1615	Assy,Connector-S,5P	1
CA603	620 201 1622	Assy,Connector-S,2P	1
CA604	620 201 1639	Assy,Connector-S,3P	1
PL602	620 030 8083	Lamp	1
SW601	620 201 2353	Switch,Tact 160G (EJECT 1)	1
SW602	620 201 2353	Switch,Tact 160G (EJECT 2)	1
SW603	620 201 2353	Switch,Tact 160G (EJECT 3)	1
SW604	620 201 2353	Switch,Tact 160G (EJECT 4)	1
SW605	620 201 2353	Switch,Tact 160G (EJECT 5)	1
SW606	620 201 2353	Switch,Tact 160G (SCAN FWD)	1
SW607	620 201 2353	Switch,Tact 160G (SCAN BACK)	1
SW608	620 201 2353	Switch,Tact 160G (F.FWD)	1
SW609	620 201 2353	Switch,Tact 160G (F.BACK)	1
SW610	620 201 2353	Switch,Tact 160G (STOP)	1
SW611	620 201 2353	Switch,Tact 160G (PLAY)	1
SW612	620 201 2353	Switch,Tact 160G (PAUSE)	1
Q601	405 004 5103	TR 2SA608-G-SPA-AC	1
Q602	405 004 5103	TR 2SA608-G-SPA-AC	1
D601	407 125 8209	DIODE HSS271	1
or	407 008 0405	DIODE GMB01-BT	1
D602	407 125 8209	DIODE HSS271	1
or	407 008 0405	DIODE GMB01-BT	1
D603	407 125 8209	DIODE HSS271	1
or	407 008 0405	DIODE GMB01-BT	1
D604	407 125 8209	DIODE HSS271	1
or	407 008 0405	DIODE GMB01-BT	1
D605	407 125 8209	DIODE HSS271	1
or	407 008 0405	DIODE GMB01-BT	1
D606	407 125 8209	DIODE HSS271	1
or	407 008 0405	DIODE GMB01-BT	1
D607	407 125 8209	DIODE HSS271	1
or	407 008 0405	DIODE GMB01-BT	1

Ref. No.	Part No.	Description	Q'ty
D608	407 125 8209	DIODE HSS271	1
or	407 008 0405	DIODE GMB01-BT	1
D609	407 125 8209	DIODE HSS271	1
or	407 008 0405	DIODE GMB01-BT	1
R601	401 025 8208	CARBON 22K JA 1/6W	1
R602	401 024 7400	CARBON 10K JA 1/6W	1
R603	401 027 0309	CARBON 47K JA 1/6W	1
R604	401 025 8208	CARBON 22K JA 1/6W	1
R605	401 024 7400	CARBON 10K JA 1/6W	1
R606	401 027 0309	CARBON 47K JA 1/6W	1
ASSY,PCB,POWER SWITCH			
47	620 203 9695	Assy,PCB,Power Switch	1
	620 202 3472	Terminal,Wrapper,2P	1
	620 053 6905	Cover Safety	1
S901	⚠ 620 015 2358	Power Switch	1
C401	⚠ 620 006 6679	Capacitor 0.01MF400V	1

NOTES:

1. Parts order must contain Model Number, Part Number and Description.
2. Ordering quantity of screws and resistors must be multiple of 10 pcs.

PRODUCT SAFETY NOTICE

Each precaution in this manual should be followed during servicing. Components identified with the IEC symbol ⚠ in the parts list and the schematic diagram designate components in which safety can be of special significance. When replacing a component identified with ⚠, use only the replacement parts designated, or parts with the same ratings of resistance, wattage or voltage that are designated in the parts list in this manual. Leakage-current or resistance measurements must be made to determine that exposed parts are acceptably insulated from the supply circuit before returning the product to the customer.

CD PLAYER ADJUSTMENT PROCEDURES

BEFORE CHECKING OR ADJUSTING CD PLAYER

1. Procedures for all adjustments for the CD player from start to finish are described below.
2. If no problems are found after each item is checked when the pick-up is replaced, there is no need to adjust all items again.

SETTING OF INITIAL POSITION OF VOLUME

1. Set the variable resistors to the initial positions listed below:

VR101 (FOCUS OFFSET)	Mechanical Center
VR102 (E/F BALANCE)	Mechanical Center
VR103 (TRACKING OFFSET)	Mechanical Center
VR104 (TRACKING GAIN)	Mechanical Center
VR105 (KICK GAIN)	Mechanical Center
VR106 (FOCUS GAIN)	Mechanical Center

MASTER CLOCK CHECKING

1. Since this adjustment Sets standard time for the total system, be sure to adjust before operation.
2. Connect the frequency counter between the **IC105 (4pin)** and to **GND.**
3. Check the frequency counter reads 16.9344MHz ±300p.p.m.

PLL (VCO) FREE RUN FREQUENCY ADJUSTMENT

1. Connect the frequency counter between the **T105 (CK)** and to **GND.** (Use a 10:1 probe)
2. Push the POWER button to switch the power on and push the STOP button.
3. Adjust the OSC coil L103 using a plastic screwdriver until the frequency counter indicator reads 4.3218MHz ±10kHz.

DSP SYSTEM CLOCK CHECKING

1. Connect the frequency counter between the test point **X IN** (IC YM3815) of **R362** lead and to **GND.**
2. Check the frequency counter reads 8.6436MHz.

FOCUS OFFSET ADJUSTMENT

1. Push the POWER button to switch the power on and push the DISC EJECT button to open the Disc Tray and remove the disc.
2. Push the DISC EJECT button to close the Disc Tray and push the STOP button.
3. Connect a DC Voltmeter to the **T103 (FEO)** and to **GND.**
4. In this condition check that the DC Voltmeter indicator is in the range 0V±20mV, and adjust VR101 if it is not.

TRACKING OFFSET ADJUSTMENT

1. Push the POWER button to switch the power on and push the STOP button.
2. Connect a DC Voltmeter to the **T101 (T-COIL)** and to **GND.**
3. In this condition check that the DC Voltmeter indicator is in the range 0V±50mV, and adjust VR103 if it is not.

NOTE:
Perform this adjustment once again after adjusting the E/F BALANCE and TRACKING GAIN signals.

CONFIRMING HF LEVEL

1. PLAY the fourth item on the test disc (Modern Wave Ⅱ).
2. Connect an oscilloscope to the **T104 (HF)** pin, and check that its HF level is in the range 2.6±0.5V(p-p).
3. If the results of the above procedure are not satisfactory, the Pick-up is damaged.

E/F BALANCE ADJUSTMENT

1. Place the test disc (Modern Wave Ⅱ) on the Disc Tray, and play the fourth item on the disc. Short the test point **TP TEST** pins on the μ-con Control P.C.Board to the TEST mode.
2. Short the **T102 (TROF)** pin to **GND** to turn tracking servo OFF.
3. Connect a DC Voltmeter and an oscilloscope via the low-pass filter like that shown in the illustration below to the test terminal **T102 (TE)**(tracking error) pin.



Measurement circuit

4. Adjust VR102 so that the DC Voltmeter reading is 0V±45mV (oscilloscope waveform is symmetric to + and − about the zero level).

CD PLAYER ADJUSTMENT PROCEDURES (Continued)

FOCUS GAIN ADJUSTMENT

1. Apply VR106 to the position of Mechanical center position, and place the test disc (Modern Wave Ⅱ) on the Disc Tray.
2. Push the POWER button to switch the power on and PLAY the first item on the test disc. Now apply a signal of 1kHz and 0.3Vp-p from the signal generator to the **T101 (F+)** and oscilloscope (CH1).
3. Connect an oscilloscope (CH2) to the **T101 (F−)** pin and to **GND.**
4. Set the oscilloscope to X-Y operation, and while observing the lissajous waveform adjust VR106 to the point where the phase difference is 90° as shown in Fig. 1 below.



Fig.1

KICK GAIN ADJUSTMENT

1. Place the test disc (Modern Wave Ⅱ) on the Disc Tray.
2. Set the oscilloscope to NORMAL TRIG., set the EXT. TRIG. pin to external trigger, and input the trigger from test point **T105 (THLD)** pin to the oscilloscope.
3. Next connect test point **T102 (TE)** pin to Channel 1 of the oscilloscope.
4. Push the POWER button to switch the power on and PLAY the first item on the test disc, and the push the PAUSE button. Now observe the waveform for TE with trigger applied from test point **T105 (THLD)** pin. At this point, adjust VR105 so that a kick pulse waveform of about 1 to 1.3 tracks as shown in Fig. 2 below is obtained.



Fig.2

TRACKING GAIN ADJUSTMENT

1. Apply VR104 to the position of Mechanical center position, and place the test disc (Modern Wave Ⅱ) on the Disc Tray.
2. Push the POWER button to switch the power on and PLAY the first item on the test disc. Now apply a signal of 1250Hz and 0.3Vp-p from the signal generator to the **T105 (T+)** and oscilloscope (CH1).
3. Connect an oscilloscope (CH2) to the **T101 (T−)** pin and to **GND.**
4. Set the oscilloscope to X-Y operation, and while observing the lissajous waveform adjust VR104 to the point where the phase difference is 90° as shown in Fig. 1 above.

NOTE:
If these two adjustments are performed, the TRACKING OFFSET must also be adjusted.

IC & TRANSISTOR DC VOLTAGES

IC PIN NUMBERS DC VOLTAGES																					
Ref. No.	**DEVICE**	**1**	**2**	**3**	**4**	**5**	**6**	**7**	**8**	**9**	**10**	**11**	**12**	**13**	**14**	**15**	**16**	**17**	**18**	**19**	**20**
IC101	LA9200NM	0V	0V	0V	0V	0V	0V	0V	8.0V	0V	0V	0V	0V	0V	0V	0V	4.2V	4.0V	4.2V	−5.0V	1.2V
		21	**22**	**23**	**24**	**25**	**26**	**27**	**28**	**29**	**30**	**31**	**32**	**33**	**34**	**35**	**36**	**37**	**38**	**39**	**40**
		5.0V	2.0V	2.0V	2.0V	0V	2.4V	0V	2.4V	1.2V	0V	0.4V	0.2V	0.1V	1.0V	0V	−0.1V	0V	0V	8.2V	5.0V
		41	**42**	**43**	**44**	**45**	**46**	**47**	**48**	**49**	**50**	**51**	**52**	**53**	**54**	**55**	**56**	**57**	**58**	**59**	**60**
		0V	0V	−5.0V	0V	0V	0V	0V	0V	–	–	–	–	–	–	–	–	–	–	–	–

IC PIN NUMBERS DC VOLTAGES																					
Ref. No.	**DEVICE**	**1**	**2**	**3**	**4**	**5**	**6**	**7**	**8**	**9**	**10**	**11**	**12**	**13**	**14**	**15**	**16**	**17**	**18**	**19**	**20**
IC102	YM3815-H	5.0V	2.7V	2.1V	2.4V	0V	2.0V	2.0V	2.0V	0V	0V	0V	0V	0V	4.2V	0V	4.0V	4.2V	4.8V	0V	5.0V
		21	**22**	**23**	**24**	**25**	**26**	**27**	**28**	**29**	**30**	**31**	**32**	**33**	**34**	**35**	**36**	**37**	**38**	**39**	**40**
		0V	0V	0V	5.0V	0.5V	0V	1.5V	1.4V	0.2V	0V	0.2V	5.0V	5.0V	1.5V	0V	0V	0V	5.0V	5.0V	2.4V
		41	**42**	**43**	**44**	**45**	**46**	**47**	**48**	**49**	**50**	**51**	**52**	**53**	**54**	**55**	**56**	**57**	**58**	**59**	**60**
		0V	2.3V	2.3V	2.3V	2.3V	2.3V	2.3V	2.3V	2.2V	2.7V	4.6V	2.7V	1.5V	1.5V	0.9V	0.9V	3.9V	4.0V	4.0V	1.1V
		61	**62**	**63**	**64**	**65**	**66**	**67**	**68**	**69**	**70**	**71**	**72**	**73**	**74**	**75**	**76**	**77**	**78**	**79**	**80**
		0.7V	0.7V	3.2V	3.1V	0V	1.5V	1.5V	1.6V	4.7V	1.7V	1.8V	1.8V	1.8V	1.8V	1.9V	1.8V	1.9V	1.9V	1.9V	1.6V

IC PIN NUMBERS DC VOLTAGES																					
Ref. No.	**DEVICE**	**1**	**2**	**3**	**4**	**5**	**6**	**7**	**8**	**9**	**10**	**11**	**12**	**13**	**14**	**15**	**16**	**17**	**18**	**19**	**20**
IC103	LC3517AM-15	2.4V	2.4V	2.4V	2.3V	2.3V	2.3V	2.4V	2.3V	4.2V	0.6V	4.0V	0V	4.0V	3.9V	0.9V	1.0V	0.9V	0V	–	2.8V
		21	**22**	**23**	**24**	**25**	**26**	**27**	**28**	**29**	**30**	**31**	**32**	**33**	**34**	**35**	**36**	**37**	**38**	**39**	**40**
		4.6V	2.5V	2.3V	5.0V	–	–	–	–	–	–	–	–	–	–	–	–	–	–	–	–

IC PIN NUMBERS DC VOLTAGES																					
Ref. No.	**DEVICE**	**1**	**2**	**3**	**4**	**5**	**6**	**7**	**8**	**9**	**10**	**11**	**12**	**13**	**14**	**15**	**16**	**17**	**18**	**19**	**20**
IC104	YM3613C	5.0V	0V	2.1V	1.5V	1.1V	4.3V	2.1V	1.8V	2.4V	0V	4.3V	0V	5.0V	0V	0V	0V	3.2V	2.4V	1.5V	1.7V
		21	**22**	**23**	**24**	**25**	**26**	**27**	**28**	**29**	**30**	**31**	**32**	**33**	**34**	**35**	**36**	**37**	**38**	**39**	**40**
		0V	0V	1.3V	4.3V	–	–	–	–	–	–	–	–	–	–	–	–	–	–	–	–

IC PIN NUMBERS DC VOLTAGES																
Ref. No.	**DEVICE**	**1**	**2**	**3**	**4**	**5**	**6**	**7**	**8**	**9**	**10**	**11**	**12**	**13**	**14**	**15**	**16**
IC105	PD0050	2.3V	2.4V	5.0V	2.0V	2.4V	0V	1.9V	0V	0V	2.4V	0V	0V	5.0V	3.3V	2.1V	5.0V
IC106	TC4075B	0V	0V	5.0V	0V	0V	4.9V	0V	5.0V	5.0V	0V	0V	0V	0V	5.0V	–	–
IC107	TC4049BP	5.0V	5.0V	9.5V	5.0V	9.6V	5.0V	9.7V	0V	0V	4.9V	5.0V	0V	0V	5.0V	0V	0V

IC PIN NUMBERS DC VOLTAGES									
Ref. No.	**DEVICE**	**1**	**2**	**3**	**4**	**5**	**6**	**7**	**8**
IC108	NJM4558	0.5V	0V	0V	−10.5V	0V	0V	0V	10.3V
IC109	NJM4558	0.4V	0V	0V	−10.5V	0V	0V	0V	10.3V
IC110	NJM4558	0V	0V	0V	−10.5V	0V	0V	0V	10.3V
IC111	NJM4558	0.5V	0V	0V	−10.5V	0V	0V	−0.6V	10.3V
IC112	STA341M	10.3V	−0.6V	0.5V	0.5V	−10.5V	−8.4V	0V	0V

IC PIN NUMBERS DC VOLTAGES																					
Ref. No.	**DEVICE**	**1**	**2**	**3**	**4**	**5**	**6**	**7**	**8**	**9**	**10**	**11**	**12**	**13**	**14**	**15**	**16**	**17**	**18**	**19**	**20**
IC115	LC74HC241	4.9V	0V	0V	0V	0V	0V	0V	0V	0V	0V	0V	2.4V	0V	2.4V	0V	2.3V	0V	2.4V	5.0V	5.0V
IC116	LA6510	0V	0V	0V	0V	−14.8V	0V	0V	0V	0V	14.0V	–	–	–	–	–	–	–	–	–	–

IC & TRANSISTOR DC VOLTAGES (Continued)

IC PIN NUMBERS DC VOLTAGES																					
Ref. No.	**DEVICE**	**1**	**2**	**3**	**4**	**5**	**6**	**7**	**8**	**9**	**10**	**11**	**12**	**13**	**14**	**15**	**16**	**17**	**18**	**19**	**20**
IC117	LC6538D	−17.0V	−25.6V	−23.2V	−23.1V	−23.1V	−23.1V	−23.1V	−22.0V	−23.1V	−19.8V	−23.1V	−23.1V	−23.1V	−23.1V	5.0V	1.7V	2.7V	0V	0V	4.8V
		21	**22**	**23**	**24**	**25**	**26**	**27**	**28**	**29**	**30**	**31**	**32**	**33**	**34**	**35**	**36**	**37**	**38**	**39**	**40**
		1.5V	1.8V	0V	0V	0V	0V	0V	0V	2.5V	5.0V	0.2V	0V	0V	0V	4.9V	4.4V	0V	0V	0V	0V
		41	**42**	**43**	**44**	**45**	**46**	**47**	**48**	**49**	**50**	**51**	**52**	**53**	**54**	**55**	**56**	**57**	**58**	**59**	**60**
		0V	0V	5.0V	4.9V	0V	4.6V	4.9V	4.9V	4.9V	4.0V	0V	0V	0V	−6.0V	0.5V	−6.1V	−19.4V	0.3V	−6.3V	−6.2V
		61	**62**	**63**	**64**	**65**	**66**	**67**	**68**	**69**	**70**	**71**	**72**	**73**	**74**	**75**	**76**	**77**	**78**	**79**	**80**
		−19.3V	−26.0V	−15.8V	−13.6V	–	–	–	–	–	–	–	–	–	–	–	–	–	–	–	–

IC PIN NUMBERS DC VOLTAGES																	
Ref. No.	**DEVICE**	**1**	**2**	**3**	**4**	**5**	**6**	**7**	**8**	**9**	**10**	**11**	**12**	**13**	**14**	**15**	**16**
IC118	TC74HCU04	4.6V	0V	0V	5.0V	0V	5.0V	0V	0V	4.8V	0V	5.0V	5.0V	0V	5.0V	–	–
IC119	LA6501-LR	0V	0V	−14.9V	0V	14.0V	–	–	–	–	–	–	–	–	–	–	–
IC123,124	PCM56P	−12.1V	0V	12.1V	0.7V	2.2V	3.3V	0V	−11.7V	0V	0V	0V	0V	0V	−9.6V	−4.7V	12.2V
IC128	NJM4558D	0V	0V	0V	−12.2V	0V	0V	0V	12.3V	–	–	–	–	–	–	–	–

IC PIN NUMBERS DC VOLTAGES									
Ref. No.	**DEVICE**	**1**	**2**	**3**	**4**	**5**	**6**	**7**	**8**
IC901	NJM2043DD	0V	0V	0V	−12.3V	0V	0V	−1.2V	12.3V
IC902	NJM78M05	5.0V	0V	14.1V	–	–	–	–	–
IC903	NJM78M05	5.0V	0V	7.5V	–	–	–	–	–
IC904	TA79L005P	−5.0V	−10.5V	0V	–	–	–	–	–

TRANSISTOR DC VOLTAGES									
Ref. No.	**DEVICE**	**B**	**C**	**E**	**Ref. No.**	**DEVICE**	**B**	**C**	**E**
Q901	2SK246	17.4V	12.9V	12.9V	Q906	2SA608	4.8V	−7.6V	4.9V
Q902	2SD1913	12.9V	17.4V	12.3V	Q908	2SD1913	11.0V	14.1V	10.3V
Q903	2SK246	−12.9V	−17.6V	−17.6V	Q909	2SB1274	−11.1V	−14.9V	−10.5V
Q904	2SB1274	−12.9V	−17.6V	−12.3V	Q910	2SB911	−26.5V	−36.7V	−26.0V

FL P.C.BOARD
(BOTTOM VIEW)



SWITCH LEFT P.C.BOARD
(BOTTOM VIEW)



TRANS P.C.BOARD
(BOTTOM VIEW)

SWITCH RIGHT P.C.BOARD
(BOTTOM VIEW)



MAIN P.C.BOARD & HEADPHONE P.C.BOARD
(BOTTOM VIEW)



WIRING DIAGRAM



SCHEMATIC DIAGRAM (1)



SCHEMATIC DIAGRAM (2)







IC & TRANSISTOR LEAD IDENTIFICATION

TRANSISTOR	FRONT VIEW	BOTTOM VIEW	TRANSISTOR	FRONT VIEW	BOTTOM VIEW
2SA608 2SC536			DTA114		
2SB1274 2SD1913			2SA1317 2SA1346 2SA608 2SD1012		
2SK246			2SB911 2SD1227		

TERMINAL NAME

B → BASE
C → COLLECTOR
E → EMITTER
S → SOURCE
G → GATE
D → DRAIN

NJM4556S FRONT/SIDE VIEWS



LA6510 FRONT/SIDE VIEWS



NJM2043DD TOP VIEW
NJM4558 TOP VIEW



TC4075B TOP VIEW
TC74HCU04P TOP VIEW



TC4049BP TOP VIEW



IC & TRANSISTOR LEAD IDENTIFICATION (Continued)

PCM56P TOP VIEW
PD0050 TOP VIEW



LC74HC241 TOP VIEW



YM3613C TOP VIEW



LC6538D-4215 TOP VIEW



TA79L005P FRONT/SIDE VIEWS



LC3517AM-15 TOP/SIDE VIEWS



LA9200NM TOP/SIDE VIEWS



NJM78M05FA FRONT/SIDE VIEWS



LA6501-LR FRONT/SIDE VIEWS



STA341M FRONT/SIDE VIEWS



YM3815-H TOP/SIDE VIEWS



IC BLOCK DIAGRAM

NJM4556S BLOCK DIAGRAM



LA6510 BLOCK DIAGRAM



NJM2043DD BLOCK DIAGRAM



NJM4558 BLOCK DIAGRAM



TC4075B BLOCK DIAGRAM



TC74HCU04P BLOCK DIAGRAM



TC4049BP BLOCK DIAGRAM



PCM56P BLOCK DIAGRAM


MSB
+Vcc VREF ADJ IOUT GND S.J RF VOUT
16 15 14 13 12 11 10 9
16 BIT CURRENT OUTPUT DA CONVERTER
16 BIT LATCH
16 BIT SERIAL TO PARALLEL CONVERSION
LEVEL SHIFT AND CONTROL LOGIC
1 2 3 4 5 6 7 8
-Vcc GND +VL N/C CK LEC DATA -VL

PD0050 BLOCK DIAGRAM



IC BLOCK DIAGRAM (Continued)

LC74HC241 BLOCK DIAGRAM



YM3613C BLOCK DIAGRAM



LC6538D-4215 BLOCK DIAGRAM



IC BLOCK DIAGRAM (Continued)

TA79L005P BLOCK DIAGRAM



LC3517AM-15 BLOCK DIAGRAM



LA9200NM BLOCK DIAGRAM



IC BLOCK DIAGRAM (Continued)

NJM78M05FA BLOCK DIAGRAM



LA6501-LR BLOCK DIAGRAM



STA341M BLOCK DIAGRAM



IC BLOCK DIAGRAM (Continued)

YM3815-H BLOCK DIAGRAM



Printed in Japan